











Turn Main Power off before Installation

Do not remove the cover during use.



Max. 12pcs interconnected

Please Note:

1. Please check whether the lamp is fixed and wired properly if the lamp doesn't work while switched on.
2. 4W, 7W and 9W lamp must be fixed with two clips.
13W, 18W and 22W lamp must be fixed with three clips.

ENVIRONMENTAL PROTECTION



Waste electrical & Electronic equipment regulations requires that any of our products showing this marking must not be disposed of with other household or commercial waste. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such products from other waste types and recycle it responsibly at your local facilities.

eurolux

Lighting your way

Under Counter LED Light



C284: 4W integrated LED 230V
C285: 7W integrated LED 230V
C286: 13W integrated LED 230V

PRODUCT CODE

C284 / C285 / C286

Cape Town - 9 Racecourse Road, Milnerton, 7441
Johannesburg - 10 Milkyway Avenue, Linbro Business Park, Sandton, 2065
www.eurolux.co.za

Please read instructions before commencing installation and retain for future reference.

SPECIFICATIONS

- **Fitting material:** PC
- **Lamp type:** C284 - 26 x 0.2W integrated LED (4W)
C285 - 45 x 0.2W integrated LED (7W)
C286 - 76 x 0.2W integrated LED (13W)
The light source of this luminaire is not replaceable. When the light source reaches its end of life the whole luminaire should be replaced, or the light source should only be replaced by the manufacturer.
- **Lifetime:** 25 000 Hours
- **Dimensions:** C284 - (L)288mm x (W)36mm x (D)28mm
C285 - (L)516mm x (W)36mm x (D)28mm
C284 - (L)849mm x (W)36mm x (D)28mm
- **Voltage:** 220V - 240V ~ 50Hz
- **Protection against electric shock:** Class 2. Does not require earthing.
- **IP rating:** IP 20
- Commercial / domestic use.
- Not suitable for outdoor use.
- Not for use in areas exposed to moisture.
- Non dimmable.

IMPORTANT SAFEGUARDS

Attachments:

If the external flexible cable or cord of this luminaire is damaged, it should be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard. To ensure that you get maximum longevity and maximum use out of your luminaire, please observe the following safety instructions.



Electrical products can cause death, injury, or damage to property. Installation of the luminaire must be carried out by a qualified electrician, in accordance with SANS 10142. On completion of installation, ensure that the Certificate of Compliance is updated.

- Before connecting this luminaire, ensure that voltage indicated on the rating label corresponds with the mains voltage in your home.
- This luminaire is checked in full for conformity to the quality standards and safety requirements.
- The manufacturer / supplier is not responsible for any damage of properties and persons, caused by the incorrect use or installation of the luminaire.
- Should you be unsure of how to install this luminaire correctly, please consult a professional electrician or your supplier for assistance.
- Ensure all items / components, threads and screws are tightly secured.

IMPORTANT:

- Tampering with this luminaire, i.e. using silicon sealers or incorrect cabling, will invalidate your warranty.
- When the protection lens is damaged, it should be replaced immediately. The luminaire must not be used without the protection lens.
- Please check whether the connection of the power cord is safe and reliable before installation.
- Always ensure that the mains supply voltage is correct.

- Ensure that you do not place the luminaire near any combustible materials and / or surfaces.
- Choking hazard: May contain small parts. Keep away from children.
- Do not insert your fingers or any part of your body into the electrical contact and sockets of this product whilst it is connected to the electricity supply.
- Item may vary slightly from the picture on the carton.
- Coastal humidity may effect the longevity of the luminaire.

INSTALLATION

- Switch the power supply off before commencing with the installation.
- When drilling is required for fixing the luminaire to the required surface please ensure that no pipes or cables are within the drilling area.
- Reconnect power supply.

CLEANING

- Before cleaning always ensure the power supply is turned off.
- Do not immerse the luminaire in water.
- No abrasive products, solvents, detergent may be used to clean this luminaire.
- Ensure that the fitting does not come in contact with corrosive chemicals, etc.
- Coastal areas ensure that the luminaire is cleaned fortnightly.